

SPARK PLUGS



BOSCH INDUSTRIAL LINE



BOSCH

7302



MR3DPP33

| | | | |
|---------------------------|------------------------------------|------------------------|-----------------------|
| 10 Digit Type Code | 0 242 356 501 | Cross Reference | |
| Hex | 7/8" (22.2mm) | Champion | RB75N / RB75PP |
| Thread | 18mm x 1,5 | Beru | 18GZ20 |
| Reach | 13/16" (20.6mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 0.8mm Platinum/ Iridium | | |
| Ground Electrode | Platinum Inlay | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 3 +/-2 Kohm | | |

7303



MR3BPP330

| | | | |
|-------------------------|------------------------------------|------------------------|---------------------|
| 10 Digit | 0 242 356 502 | Cross Reference | |
| Type Code | MR3BPP330 | Champion | RM77N/RM77PP |
| Hex | 7/8" (22.2mm) | Beru | 18GZ22 |
| Thread | 18mm x 1,5 | | |
| Reach | 1/2" (12.7mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 0.8mm Platinum/ Iridium | | |
| Ground Electrode | Platinum Inlay | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 KOhm | | |

7305



MR3DII360

| | | | |
|-------------------------|------------------------|------------------------|-------------------|
| 10 Digit | 0 242 356 503 | Cross Reference | |
| Type Code | MR3DII360 | Denso | GI3-5 |
| Hex | 7/8" (22.2mm) | Beru | 18GZ6-77-2 |
| Thread | 18mm x 1,5 | Caterpillar | 243-4291 |
| Reach | 13/16" (20.6mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 2.4mm Iridium | | |
| Ground Electrode | 2.4mm Iridium | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 KOhm | | |

7306



MR3DPP330

| | | | |
|-------------------------|------------------------------------|------------------------|----------------------|
| 10 Digit | 0 242 356 504 | Cross Reference | |
| Type Code | MR3DPP330 | Denso | GI3-1 / GI3-3 |
| Hex | 7/8" (22.2mm) | Champion | RB77WPCC / |
| Thread | 18mm x 1,5 | | KB77WPCC/ |
| Reach | 13/16" (20.6mm) | | RB77CC / |
| Heat Range | 3 | | RB77WPC |
| Center Electrode | 2.0mm Platinum/ Iridium | Beru | 18GZ6-77 |
| Ground Electrode | Platinum Inlay | Caterpillar | 194-8518 |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 3 +/-2 KOhm | | |

7307



MR3DII330

| | | | |
|-------------------------|------------------------|------------------------|----------------------|
| 10 Digit | 0 242 356 507 | Cross Reference | |
| Type Code | MR3DII330 | Denso | GL3-1 / GL3-3 |
| Hex | 13/16" (20.8mm) | Champion | RB75WPCC |
| Thread | 18mm x 1,5 | | |
| Reach | 13/16" (20.6mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 2.0mm Iridium | | |
| Ground Electrode | Platinum Inlay | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 3 +/-2 Kohm | | |

7308



MR3DII360

| | | | |
|-------------------------|------------------------|------------------------|-------------------|
| 10 Digit | 0 242 356 508 | Cross Reference | |
| Type Code | MR3DII360 | | |
| Hex | 13/16" (20.8mm) | Denso | GL3-5 |
| Thread | 18mm x 1,5 | Beru | 18GZ5-77-2 |
| Reach | 13/16" (20.6mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 2.4mm Iridium | | |
| Ground Electrode | 2.4mm Iridium | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 Kohm | | |

7 3 1 1



WR3CPP33

| | | | |
|-------------------------|------------------------------------|------------------------|-----------------|
| 10 Digit | 0 242 255 512 | Cross Reference | |
| Type Code | WR3CPP33 | | |
| Hex | 13/16" (20.8mm) | Denso | GE3-1 |
| Thread | 14mm x 1,25 | Champion | RN79G |
| Reach | 3/4" (19mm) | Beru | 14R-4CDP |
| Heat Range | 3 | Caterpillar | 2N2839 |
| Center Electrode | 2.0mm Platinum/ Iridium | | |
| Ground Electrode | Platinum Inlay | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 Kohm | | |

7 3 1 3



WR7CE

| | | | |
|-------------------------|----------------------------|------------------------|-------------|
| 10 Digit | 0 242 236 580 | Cross Reference | |
| Type Code | WR7CE | | |
| Hex | 13/16" (20.8mm) | Champion | RN5C |
| Thread | 14mm x 1.25 | | |
| Reach | 3/4" (19mm) | | |
| Heat Range | 7 | | |
| Center Electrode | Copper with Yttrium | | |
| Ground Electrode | Nickel | | |
| Gap | 0.020" (0.5mm) | | |
| Resistance | 6 +/-3 KOhm | | |

7 3 1 5



WR3CII360

| | | | |
|-------------------------|------------------------|------------------------|-------------------|
| 10 Digit | 0 242 255 519 | Cross Reference | |
| Type Code | WR3CII360 | | |
| Hex | 13/16" (20.8mm) | Denso | GE3-5 |
| Thread | 14mm x 1.25 | Beru | 14R-4CIU-2 |
| Reach | 3/4" (19mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 2.4mm Iridium | | |
| Ground Electrode | 2.4mm Iridium | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 KOhm | | |

7 3 2 1



FR3KII332

| | | | |
|-------------------------|-----------------------|------------------------|----------------------|
| 10 Digit | 0 242 255 511 | Cross Reference | |
| Type Code | FR3KII332 | Denso | GK3-1 / GK3-3 |
| Hex | 5/8" (16mm) | Champion | RC78PYP / |
| Thread | 14mm x 1.25 | | RC78PYP15/ |
| Reach | 3/4" (19mm) | | RC78WYP |
| Heat Range | 3 | Beru | 14FR-4DPU0 |
| Center Electrode | 1.25mm Iridium | | |
| Ground Electrode | Platinum Inlay | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 KOhm | | |

7 3 2 2



FR3CII360

| | | | |
|-------------------------|-----------------------|------------------------|------------------|
| 10 Digit | 0 242 255 518 | Cross Reference | |
| Type Code | FR3CII360 | | |
| Hex | 5/8" (16mm) | Denso | GK3-5 |
| Thread | 14mm x 1.25 | Beru | 14FR-4DIU |
| Reach | 3/4" (19mm) | | |
| Heat Range | 3 | | |
| Center Electrode | 2.4mm Iridium | | |
| Ground Electrode | 2.4mm Iridium | | |
| Gap | 0.012" (0.3mm) | | |
| Resistance | 6 +/-3 KOhm | | |